



## Shift out LED kit (SKU:DFR0089)

---

### Contents

- [1 Introduction](#)
- [2 Specification](#)
- [3 Pin Usage](#)
- [4 Sample Code](#)

### Introduction



This shiftout LED Kit includes a very simple and small LED display module. It makes it possible for you to directly connect many 7-segment led modules in a chain. So you could diy a simple timer or a clock display , and many other devices that require the use of 7 segment LEDs.

### Specification

- supply power:5V
- Interface: SPI
- Common Anode
- Digital Bits: 1
- number of connecting:over 16
- Directly connected with the interface shield
- Compatible with the SPI LED Module 8 Digital (Arduino Compatible)
- size:41x30x25mm

### Pin Usage

Shiftout register:Digital pins 3, 8, and 9

## Sample Code

```
//Pin connected to latch pin (ST_CP) of 74HC595
const int latchPin = 8;

//Pin connected to clock pin (SH_CP) of 74HC595
const int clockPin = 3;

////Pin connected to Data in (DS) of 74HC595
const int dataPin = 9;
byte Tab[]={
    0xc0,0xf9,0xa4,0xb0,0x99,0x92,0x82,0xf8,0x80,0x90,0xff};
void setup() {
    //set pins to output because they are addressed in the main loop
    pinMode(latchPin, OUTPUT);
    pinMode(dataPin, OUTPUT);
    pinMode(clockPin, OUTPUT);
    Serial.begin(9600);
    Serial.println("reset");
    for(int i = 0;i < 10; i++){
        digitalWrite(latchPin, LOW);
        shiftOut(dataPin, clockPin, MSBFIRST, Tab[i]);
        digitalWrite(latchPin, HIGH);
        delay(500);
    }
}

void loop() {
    if (Serial.available() > 0) {
        // ASCII '0' through '9' characters are
        // represented by the values 48 through 57.
        // so if the user types a number from 0 through 9 in ASCII,
        // you can subtract 48 to get the actual value:
        int bitToSet = Serial.read() - 48;
        // write to the shift register with the correct bit set high:
        digitalWrite(latchPin, LOW);
        // shift the bits out:
        shiftOut(dataPin, clockPin, MSBFIRST, Tab[bitToSet]);
    }
}
```

```
// turn on the output so the LEDs can light up:  
digitalWrite(latchPin, HIGH);  
}  
}
```